

*AC mV output, 20 A/200 A, 10 mV/A, 1mV/A
For 3 phase power analyzer DW-6093, DW-6095*

200 A CURRENT PROBE

Model : CP-200

ISO-9001, CE, IEC1010



Lutron

LUTRON ELECTRONIC

The Art of Measurement

2000 Amp current probe

Model : CP-2000

- * Range : 20 A/200 A/2000 A.
- * Output sensitivity : 100 mV/A, 10 mV/A, 1 mV/A.
- * Output voltage : 2 ACV (20 A, 200 A, 2000 A).
- * Max. conductor size : 51 mm (2.1 inch) Dia.
- * Operation frequency ; 50 Hz/60 Hz.
- * Optional current probe for DW-6093, DW-6095.
- * When change the new probe, the calibration procedures are not necessary.
- * Output cable : 4 meters wire, used the banana plugs, durable and safety.
- * Power supply is from the meter, battery is not necessary.



1200 Amp current probe

Model : CP-1201

- * Range : 20 A/200 A/1200 A.
- * Output sensitivity : 10 mV/A, 1 mV/A, 0.1 mV/A.
- * Output voltage : 200 ACmV (20 A, 200 A), 120 ACmV (1200 A).
- * Max. conductor size : 48 mm (1.9 inch) Dia.
- * Operation frequency : 50 Hz/60 Hz.
- * Standard (included) current probe for DW-6093, DW-6095.
- * Optional current probes for DW-6093, DW-6095.
- * When change the new probe, the calibration procedures are not necessary.
- * Output cable : 4 meters wire, used the banana plugs, durable and safety.
- * Power supply is from the meter, battery is not necessary.



200 Amp current probe

Model : CP-200

- * Range : 20 A/200 A.
- * Output sensitivity : 10 mV/A, 1 mV/A.
- * Output voltage : 200 ACmV (20 A, 200 A).
- * Max. conductor size : 19 mm (0.75 inch) Dia.
- * Operation frequency : 50 Hz/60 Hz.
- * Optional current probes for DW-6093, DW-6095.
- * When change the new probe, the calibration procedures are not necessary.
- * Output cable : 1.5 meters wire, used the banana plugs, durable and safety.
- * Battery is not necessary.

