



GASTRANSMITTER

GTR 196





Application

The gas transmitter ADOS GTR 196 is suitable for continuous measurement of gases in normal areas and areas where there are risks of explosion.

By employing 5 different types of sensor, noxious, explosive and non-combustible gases and vapours can be measured.

A current signal is generated that is proportional to the measured concentration of gas, which is transmitted to an evaluation unit placed in a safe area, away from any dangers of explosion.


The type test of the explosion-protected gas transmitter, is completed by the KEMA.

KEMA test certificate: KEMA 03 ATEX 2403 X

Degree of protection: EEx dme [ia] IIC T6

Fields of Application

- Chemical industry
- Manufacture of paints and varnishes
- Plastic processing plants
- Sewage works
- Gas-fired boiler systems
- Liquid gas storage houses
- Laboratories
- Oxygen concentration measurement
- Refineries
- Cold-storage houses (Ammonia monitoring)
- Paint spraying booths
- and many more




- 1 = Circuit voltage
- 2 = Heating voltage
- 3 = Load resistor

The TGS sensor

The **TGS sensor** contains a semiconductor sensor, which is constructed on SnO₂-sintered N-substrate.

When combustible or reducing gases are absorbed by the surface of the sensor, the concentration of the test gas is determined by the change in conductivity.




- 1 = Catalyzer pellistor
- 2 = Electric connections
- 3 = Inert pellistor
- 4 = Diffusion filter

The VQ sensor

The head of the **VQ sensor** functions on the principle of heat reaction. When combustible or reducing gases or vapours come in contact with the measuring element, they are subjected to catalytic combustion, which causes a rise in temperature; this rise causes a change in the resistance of the measuring element which is used as a measure of the component of gas being tested.

The inert element is for compensating the temperature and conductivity of the test gas.




- 1 = Diffusion filter
- 2 = Test resistor
- 3 = Comparison resistor

The GOW sensor

The **GOW sensor** functions on the principle of thermal conductivity. Two rhenium-tungsten resistors are used as a measuring element, where the comparison element is subjected to normal ambient air and the measuring element is subjected to the test gas. Any change in the concentration of gas at the measurement element, causes a change in temperature, which is due to the variation of conductivity.

The resultant change in resistance is a direct measure of the gas concentration.




- 1 = Anode
- 2 = Electrolyte
- 3 = Cathode
- 4 = Diffusion path
- 5 = Diffusion filter
- 6 = Test gas

The TOX sensor

The **TOX sensor** is a measurement system with electro-chemical cell, where the sampled gas is measured by diffusion.

In the case of oxygen measurement the oxygen content is reduced in an electrolyte, thus producing a small flow of current (electro-chemical process).

At a constant air pressure, this current is directly proportional to the oxygen concentration in the sampled air.



- 1 = Infrared-radiation source
- 2 = Test gas
- 3 = Diffusion filter
- 4 = Infrared-detector
- 5 = Measurement chamber

The IR sensor

The test gas flows through a measurement chamber that incorporates an IR radiating source and a two-channel infrared detector. The intensity of the infrared radiation is reduced as it passes through the gas molecules.

The concentration of the gas can then be calculated by the magnitude of the reduction in intensity.

Since only absorption of the wavelength (A) specific to the gas under test in relation to the wavelength (B) not absorbed by a test gas is considered, interference due to dust, ageing etc., is almost fully compensated.

The output signal of each sensor is connected to the central unit via a multicore cable for further processing. All sensors are plug-in types and thus are easily replaceable.





Technical Data

| Type | TGS | VQ | GOW | TOX | IR |
|----------------------------------|--|--|--|--|---|
| Measurement method | Semiconductor | Heat reduction | Thermal conductivity | Electro-chemical cell | Infrared |
| Measurement range | ppm ranges to 100 % LEL | ppm ranges to 100 % LEL | from 0–5 Vol % to 0–100 Vol % | ppm ranges to 0–100 Vol % | 0–100 % LEL CH ₄ , C ₃ H ₈ 0–100 Vol % CH ₄ 0–1, 2, 3, 4, 5 Vol % CO ₂ |
| Percentage error of f.s.d. | ± 5 % | ± 5 % | ± 5 % | ± 3 % | ± 3 % |
| Temperature range | -20 °C to +45 °C | -20 °C to +45 °C | -20 °C to +45 °C | -20 °C to +45 °C | -20 °C to +45 °C |
| Temperature effect | 5 % | 2 % | 2 % | 2 % | approx. 8 % |
| Response time (t ₉₀) | approx. 20 sec. | approx. 20 sec. | approx. 20 sec. | approx. 20 sec. | < 30 sec. |
| Pressure effect | 1 % | 1 % | 1 % | 1 % | 1 % |
| Mounting position | optional | optional | optional | optional | optional |
| Application | Poisonous, combustible and explosive gases in the LEL region | Poisonous, combustible and explosive gases in the LEL region | Gases exhibiting substantial differences in thermal conductivity, compared to air | O ₂ , CO, NH ₃ , NO ₂ , SO ₂ , H ₂ S and others | CH ₄ (Vol %; LEL) Propane (LEL) CO ₂ (Vol %) |
| Versions available | Single, industrial and Ex-versions | Single, industrial and Ex-versions | Industrial and Ex-versions | Industrial and Ex-versions | Industrial and Ex-versions |
| Service life of the sensor | Unlimited, when used for gases not causing catalytic poisoning | Unlimited, when used for gases not causing catalytic poisoning | Unlimited, when used which gases that do not attack aluminium, rhenium-tungsten or gold | 12 months to 5 years depending on the measuring cell | approx. 5 years |
| Supply voltage | 15 V – 30 V | 15 V – 30 V | 15 V – 30 V | 15 V – 30 V | 15 V – 30 V |
| Interface | 3-wire techniques, 4–20 mA or LON [®] 4-wire techniques, galvanically isolated, data transmission 78 kbps | 3-wire techniques, 4–20 mA or LON [®] 4-wire techniques, galvanically isolated, data transmission 78 kbps | 3-wire techniques, 4–20 mA or LON [®] 4-wire techniques, galvanically isolated, data transmission 78 kbps | 3-wire techniques, 4–20 mA or LON [®] 4-wire techniques, galvanically isolated, data transmission 78 kbps | 3-wire techniques, 4–20 mA or LON [®] 4-wire techniques, galvanically isolated, data transmission 78 kbps |
| Protection Ex-version | II 2 G EEx dme [ia] IIC T6 KEMA 03 ATEX 2403 X | II 2 G EEx dme [ia] IIC T6 KEMA 03 ATEX 2403 X | II 2 G EEx dme [ia] IIC T6 KEMA 03 ATEX 2403 X | II 2 G EEx dme [ia] IIC T6 KEMA 03 ATEX 2403 X | II 2 G EEx dme [ia] IIC T6 KEMA 03 ATEX 2403 X |
| Protection class | IP 54 | IP 54 | IP 54 | IP 54 | IP 54 |
| Dimensions (WxHxD) | 100 x 180 x 80 mm | 100 x 180 x 80 mm | 100 x 180 x 80 mm | 100 x 180 x 80 mm | 100 x 180 x 80 mm |
| Weight | 1,1 kg | 1,1 kg | 1,1 kg | 1,1 kg | 1,1 kg |